

# APC Back-UPS 700/800VA

For 1-2 PC use

BE700Y-IND/BE800-IND



- 1 Three battery back-up outlets with surge protection for computers, modems, routers etc
- 2 One surge protection-only outlet protects hardware like scanners and printers etc.
- 3 Power on button provides power to connected equipment.
- 4 Communication port in BE700Y-IND enables PC communication for graceful shutdown.
- 5 Push-button circuit breaker provides easy recovery from an overload or short circuit.
- 6 Automatic voltage regulation (AVR) instantly corrects incoming utility power without utilizing the battery.
- 7 2 Years peace of mind warranty on electronics and battery

Product feature	BE700Y-IND	BE800-IND
<b>Input</b>		
Voltage	167 Vac to 280 Vac	
Frequency	50Hz +/- 10%	
Over voltage transfer	270Vac typical (low sensitivity)	
<b>Tech Spec type</b>		
Battery backup + Surge protection outlets	700VA, 420W	800VA, 480W
Surge Protection outlet	230 Vac +/- 8%	
Voltage	On battery power 230 Vac +/- 5% (modified sine wave) on utility power 190 Vac to 250 Vac	
Frequency – On battery	50Hz / 60Hz +/- 1%	
Transfer time	5 ms typical, 10 ms max	
<b>Communication : For BE700Y-IND only. Back-UPS data port to USB on computer</b>		
<b>Protection and Filtering</b>		
Utility power surge protection	Full time, 150 joules	
EMI/RFI Filter	Full time	
Utility input	User resettable circuit breaker	
<b>Battery</b>		
Type (maintenance free)	12 V, 9 Ah	12 V, 12 Ah
<b>Physical</b>		
Net Weight	7.2 kg	9 kg
Dimensions (H x W x D)	13 cm x 22 cm x 29 cm	
Operating temperature	0° C to 40° C ( 32° F to 104° F)	
Replacement Battery Cartridge	RBC17	RBC4

Schneider Electric IT Business India Pvt. Ltd.  
4th Floor, Electra, Wing 'A'  
Prestige Tech Park  
Exora Business parks  
Marathahalli,  
Sarjapur Outer Ring Road,  
Bangalore - 560 103  
Ph : +91 80 4333 3333  
customer@apcc.com



